

QUAD19 channel list				
Mode/Channel			Value	Function
Simple 20CH	Same 10CH	Full 44CH		The selection and collocation of different mode.Simple occupies less channels,Same mode occuppies very few channels,Full is full channel operation
1	1	1		<b>Head 1 Dimmer</b>
			0..255	Dimmer 0%...100%
2	2	2		<b>Head 1 Shutter</b>
			0..31	Shutter Closed
			32..63	Shutter Open
			64..95	Strobe Effect Slow to Fast
			96..127	Shutter Open
			128..159	Pulse-effect in Sequences Slow to Fast
			160..191	Shutter Open
			192..223	Random Strobe Effect Slow to Fast
224..255	Shutter Open			
3	3	3		<b>Head 1 Red</b>
			0..255	0-100% Red Dimmer from Dark to Bright
4	4	4		<b>Head 1 Green</b>
			0..255	0-100% Green Dimmer from Dark to Bright
5	5	5		<b>Head 1 Blue</b>
			0..255	0-100% Blue Dimmer from Dark to Bright
6	6	6		<b>Head 1 White</b>
			0..255	0-100% White Dimmer from Dark to Bright
7	7	7		<b>Head 1 Macro Color</b>
			0..15	No Function
			16..31	Red
			32..47	Green
			48..63	Blue
			64..79	White
			80..95	Red+Green
			96..111	Red+Blue
			112..127	Red+White
			128..143	Green+Blue
			144..159	Green+White
			160..175	Blue+Wtihe
			176..191	R+G+B
			192..207	R+G+B+W
			208..212	2700K
			213..217	3200K
218..222	3500K			
223..227	5000K			

			228..232	5500K
			233..237	6000K
			238..242	6500K
			243..247	7000K
			248..255	8000K
8	8	8		<b>Head 1 Color Temp</b>
			0..15	No Function
			16..45	Below 3200K
			46..75	3200K - 3500K
			76..105	3500K - 5000K
			106..135	5000K - 5500K
			136..165	5500K - 6000K
			166..195	6000K - 6500K
			196..225	6500K - 7000K
226..255	7000K - 8000K			
9	9	9		<b>Head 1 Macro Run</b>
			0..15	No function
			16..31	Macro Run 1
			32..47	Macro Run 2
			48..63	Macro Run 3
			64..79	Macro Run 4
			80..95	Macro Run 5
			96..111	Macro Run 6
			112..127	Macro Run 7
			128..143	Macro Run 8
			144..159	Macro Sound 1
			160..175	Macro Sound 2
			176..191	Macro Sound 3
			192..207	Macro Sound 4
			208..223	Macro Sound 5
224..239	Macro Sound 6			
240..255	Macro Sound 7			
10	10	10		<b>Head 1 Macro Speed</b>
			0..255	Macro Speed from Slow To Fast
		11		<b>Head 1 Red1</b>
			0..255	0-100% Red1 Dimmer from Dark to Bright
		12		<b>Head 1 Green1</b>
			0..255	0-100% Green1 Dimmer from Dark to Bright
		13		<b>Head 1 Blue1</b>
			0..255	0-100% Blue1 Dimmer from Dark to Bright
14		<b>Head 1 White1</b>		
	0..255	0-100% White1 Dimmer from Dark to Bright		

		15		<b>Head 1 Red2</b>
			0..255	0-100% Red2 Dimmer from Dark to Bright
		16		<b>Head 1 Green2</b>
			0..255	0-100% Green2 Dimmer from Dark to Bright
		17		<b>Head 1 Blue2</b>
			0..255	0-100% Blue2 Dimmer from Dark to Bright
		18		<b>Head 1 White2</b>
			0..255	0-100% White2 Dimmer from Dark to Bright
		19		<b>Head 1 Red3</b>
			0..255	0-100% Red3 Dimmer from Dark to Bright
		20		<b>Head 1 Green3</b>
			0..255	0-100% Green3 Dimmer from Dark to Bright
		21		<b>Head 1 Blue3</b>
			0..255	0-100% Blue3 Dimmer from Dark to Bright
		22		<b>Head 1 White3</b>
			0..255	0-100% White3 Dimmer from Dark to Bright
11	1	23		<b>Head 2 Dimmer</b>
			0..255	Dimmer 0%...100%
				<b>Head 2 Shutter</b>
			0..31	Shutter Closed
			32..63	Shutter Open
			64..95	Strobe Effect Slow to Fast
12	2	24	96..127	Shutter Open
			128..159	Pulse-effect in Sequences Slow to Fast
			160..191	Shutter Open
			192..223	Random Strobe Effect Slow to Fast
			224..255	Shutter Open
13	3	25		<b>Head 2 Red</b>
			0..255	0-100% Red Dimmer from Dark to Bright
14	4	26		<b>Head 2 Green</b>
			0..255	0-100% Green Dimmer from Dark to Bright
15	5	27		<b>Head 2 Blue</b>
			0..255	0-100% Blue Dimmer from Dark to Bright
16	6	28		<b>Head 2 White</b>
			0..255	0-100% White Dimmer from Dark to Bright
				<b>Head 2 Macro Color</b>
			0..15	No Function
			16..31	Red
			32..47	Green
			48..63	Blue
			64..79	White
			80..95	Red+Green
			96..111	Red+Blue

17	7	29	112..127	Red+White
			128..143	Green+Blue
			144..159	Green+White
			160..175	Blue+Wtihe
			176..191	R+G+B
			192..207	R+G+B+W
			208..212	2700K
			213..217	3200K
			218..222	3500K
			223..227	5000K
			228..232	5500K
			233..237	6000K
			238..242	6500K
			243..247	7000K
248..255	8000K			
18	8	30		<b>Head 2 Color Temp</b>
			0..15	No Function
			16..45	Below 3200K
			46..75	3200K - 3500K
			76..105	3500K - 5000K
			106..135	5000K - 5500K
			136..165	5500K - 6000K
			166..195	6000K - 6500K
			196..225	6500K - 7000K
226..255	7000K - 8000K			
19	9	31		<b>Head 2 Macro Run</b>
			0..15	No function
			16..31	Macro Run 1
			32..47	Macro Run 2
			48..63	Macro Run 3
			64..79	Macro Run 4
			80..95	Macro Run 5
			96..111	Macro Run 6
			112..127	Macro Run 7
			128..143	Macro Run 8
			144..159	Macro Sound 1
			160..175	Macro Sound 2
			176..191	Macro Sound 3
			192..207	Macro Sound 4
208..223	Macro Sound 5			
224..239	Macro Sound 6			
240..255	Macro Sound 7			

20	10	32		<b>Head 2 Macro Speed</b>
			0..255	Macro Speed from Slow To Fast
		33		<b>Head 2 Red1</b>
			0..255	0-100% Red1 Dimmer from Dark to Bright
		34		<b>Head 2 Green1</b>
			0..255	0-100% Green1 Dimmer from Dark to Bright
		35		<b>Head 2 Blue1</b>
			0..255	0-100% Blue1 Dimmer from Dark to Bright
		36		<b>Head 2 White1</b>
			0..255	0-100% White1 Dimmer from Dark to Bright
		37		<b>Head 2 Red2</b>
			0..255	0-100% Red2 Dimmer from Dark to Bright
		38		<b>Head 2 Green2</b>
			0..255	0-100% Green2 Dimmer from Dark to Bright
		39		<b>Head 2 Blue2</b>
			0..255	0-100% Blue2 Dimmer from Dark to Bright
		40		<b>Head 2 White2</b>
			0..255	0-100% White2 Dimmer from Dark to Bright
41		<b>Head 2 Red3</b>		
	0..255	0-100% Red3 Dimmer from Dark to Bright		
42		<b>Head 2 Green3</b>		
	0..255	0-100% Green3 Dimmer from Dark to Bright		
43		<b>Head 2 Blue3</b>		
	0..255	0-100% Blue3 Dimmer from Dark to Bright		
44		<b>Head 2 White3</b>		
	0..255	0-100% White3 Dimmer from Dark to Bright		