



AERO WASH 710Z

DMX CHART:CH15/CH13

Mode/Channel		Value	Function
15	13		
1	1		Dimmer
		0..255	Dimmer 0%...100%
2	2		Shutter
		0..31	Shutter closed
		32..63	shutter open
		64..95	Strobe effect slow to fast
		96..127	shutter open
		128..159	Pulse-effect in sequences slow to fast
		160..191	shutter open
		192..223	Random strobe effect slow to fast
3	3		Pan
		0..255	PAN Movement
4			Pan-fine
		0..255	Fine control of Pan movement
5	4		Tilt
		0..255	Tilt Movement
6			Tile-fine
		0..255	Fine control of Tilt movement
7	5		Zoom
		0..255	In(near) to out(far)
8	6		Speed pan/tilt
		0..225	max to min speed
		226..235	blackout by movement
		236..255	no function
9	7		Red
		0..255	0-100% Red dimmer from dark to bright
10	8		Green
		0..255	0-100% Green dimmer from dark to bright
11	9		Blue
		0..255	0-100% Blue dimmer from dark to bright
12	10		White
		0..255	0-100% White dimmer from dark to bright
13	11		Macro
		0..15	No Function
		16..31	Red
		32..47	Green
		48..63	Blue
		64..79	White
		80..95	Red+Green
		96..111	Red+Blue
		112..127	Red+White
		128..143	Green+Blue
		144..159	Green+White
		160..175	Blue+White
		176..191	+RB
		192..207	R+G+B+W
		208..223	Jump effect
224..239	Fading effect		
240..255	Pulse-effect		
14	12		Macro Speed
		0..255	Macro Speed from Slow To Fast



15	13		Special function
		0..19	No function
		20..29	No function
		30..39	No function
		40..79	No function
		80..84	All Motor reset
		85..94	SCAN Motor Reset
		95..99	Zoom Motor Reset
		100..119	Internal program 1
		120..139	Internal program 2
		140..159	Internal program 3
		160..179	Internal program 4
		180..199	Internal program 5
		200..219	Internal program 6
		220..239	Internal program 7
240..255	Internal Sound program 1		

JMAZ LIGHTING

Address: 313 NEWQUIST PLACE STE B, CITY OF INDUSTRY, CA 91745 USA
 Phone: 1-626-380-0883 www.jmazlighting.com support@jmazlighting.com