



# ATTCO SPOT 100

## DMX CHART:CH13/CH11


Mode/Channel		Value	Function
16b	8b		
1	1		<b>Pan</b>
		0..255	PAN Movement
2			<b>Pan-fine</b>
		0..255	Fine control of Pan movement
3	2		<b>Tilt</b>
		0..255	Tilt Movement
4			<b>Tilt-fine</b>
		0..255	Fine control of Tilt movement
5	3		<b>Color wheel</b>
		0..14	Open / white
		15..29	Color 1
		30..44	Color 2
		45..59	Color 3
		60..74	Color 4
		75..89	Color 5
		90..104	Color 6
		105..119	Color 7
		120..127	Color8
		128..189	Forwards rainbow effect from fast to slow
		190-193	Color rotation stop
194..255	Backwards rainbow effect from slow to fast		
6	4		<b>Gobo wheel</b>
		0..9	Open
		10..19	gobo 1
		20..29	gobo 2
		30..39	gobo 3
		40..49	gobo 4
		50..59	gobo 5
		60..69	gobo 6
		70..89	Gobo 1 shake slow to fast
		90..109	Gobo 2 shake slow to fast
		110..129	Gobo 3 shake slow to fast
		130..149	Gobo 4 shake slow to fast
		150..169	Gobo 5 shake slow to fast
		170..189	Gobo 6 shake slow to fast
		190..255	Rot. gobo wheel cont. rotation slow to fast
7	5		<b>Gobo&amp;Prism rotation</b>
		0..3	no function
		4..127	Forwards gobo&prism rotation from fast to slow
		128..131	Gobo&prism rotation stop
132..255	Backwards gobo&prism rotation from slow to fast		
8	6		<b>Shutter</b>
		0..31	Shutter closed
		32..63	shutter open
		64..95	Strobe effect slow to fast
		96..127	shutter open
		128..159	Pulse-effect in sequences slow to fast
		160..191	shutter open
		192..223	Random strobe effect slow to fast
224..255	shutter open		




9	7		<b>Dimmer</b>
		0..255	Dimmer 0%...100%
10	8		<b>Focus</b>
		0..255	In(near) to out(far)
11	9		<b>Rrotating prism, Prism</b>
		0..5	OFF
		6..255	ON
12	10		<b>Speed pan/tilt</b>
		0..225	max to min speed
		226..235	blackout by movement
		236..245	blackout by all wheel changing
		246..255	no function
13	11		<b>Special function</b>
		0..19	No function
		20..29	No function
		30..39	No function
		40..79	No function
		80..84	All Motor reset
		85..87	Scan motor reset
		88..90	Colors motor reset
		91..93	Gobo motor reset
		94..96	Shutter&Dimmer motor reset
		97..99	Other motor reset
		100..119	Internal program 1
		120..139	Internal program 2
		140..159	Internal program 3
		160..179	Internal program 4
180..199	Internal program 5		
200..219	Internal program 6		
220..239	Internal program 7		
		240..255	Internal Sound program 1



Rotating Gobo Wheel



Color Wheel



	DMX Value
Gobo 1	10..19
Gobo 2	20..29
Gobo 3	30..39
Gobo 4	40..49
Gobo 5	50..59
Gobo 6	60..69

	DMX Value
Color 1	15..29
Color 2	30..44
Color 3	45..59
Color 4	60..74
Color 5	75..89
Color 6	90..104
Color 7	105..119
Color 8	120..127

# JMAZ LIGHTING

Address: 313 NEWQUIST PLACE STE B, CITY OF INDUSTRY, CA 91745 USA  
 Phone: 1-626-380-0883    [www.jmazlighting.com](http://www.jmazlighting.com)    [support@jmazlighting.com](mailto:support@jmazlighting.com)