



ATTCO SPOT 200

DMX CHART:CH14/CH16


| Mode/Channel | | Value | Function |
|--------------|--|----------|---|
| 16b | De | | |
| 1 | 1 | 0..255 | Pan PAN Movement |
| 2 | 2 | 0..255 | Pan-fine Fine control of Pan movement |
| 3 | 3 | 0..255 | Tilt Tilt Movement |
| 4 | 4 | 0..255 | Tilt-fine Fine control of Tilt movement |
| 5 | 5 | | Color wheel |
| | | 0..15 | Open / white |
| | | 16..31 | Color 1 |
| | | 32..47 | Color 2 |
| | | 48..63 | Color 3 |
| | | 64..79 | Color 4 |
| | | 80..95 | Color 5 |
| | | 96..111 | Color 6 |
| | | 112..127 | Color 7 |
| | | 128..189 | Forwards rainbow effect from fast to slow |
| 190-193 | Color rotation stop | | |
| 194..255 | Backwards rainbow effect from slow to fast | | |
| 6 | 6 | | Gobo wheel 1 |
| | | 0..9 | Open |
| | | 10..19 | gobo 1 |
| | | 20..29 | gobo 2 |
| | | 30..39 | gobo 3 |
| | | 40..49 | gobo 4 |
| | | 50..59 | gobo 5 |
| | | 60..69 | gobo 6 |
| | | 70..89 | Gobo 1 shake slow to fast |
| | | 90..109 | Gobo 2 shake slow to fast |
| | | 110..129 | Gobo 3 shake slow to fast |
| | | 130..149 | Gobo 4 shake slow to fast |
| | | 150..169 | Gobo 5 shake slow to fast |
| | | 170..189 | Gobo 6 shake slow to fast |
| | | 190..255 | Rot. gobo wheel cont. rotation slow to fast |
| 7 | 7 | | Gobo1 rotation |
| | | 0..3 | no function |
| | | 4..127 | Forwards gobo rotation from fast to slow |
| | | 128..131 | Gobo rotation stop |
| | | 132..255 | Backwards gobo rotation from slow to fast |
| 8 | 8 | | Gobo wheel 2 |
| | | 0..14 | Open |
| | | 15..29 | gobo 1 |
| | | 30..44 | gobo 2 |
| | | 45..39 | gobo 3 |
| | | 60..74 | gobo 4 |
| | | 75..89 | gobo 5 |
| | | 90..104 | gobo 6 |
| 105..119 | gobo 7 | | |



| | | | |
|--------------------|-------------------------------------|--------------|---|
| 8 | 8 | 120..134 | gobo 8 |
| | | 135..144 | Gobo 1 shake slow to fast |
| | | 145..154 | Gobo 2 shake slow to fast |
| | | 155..164 | Gobo 3 shake slow to fast |
| | | 165..174 | Gobo 4 shake slow to fast |
| | | 175..184 | Gobo 5 shake slow to fast |
| | | 185..194 | Gobo 6 shake slow to fast |
| | | 195..204 | Gobo 7 shake slow to fast |
| | | 205..214 | Gobo 8 shake slow to fast |
| | | 215..255 | Rot. gobo wheel cont. rotation slow to fast |
| 9 | 9 | | Shutter |
| | | 0..31 | Shutter closed |
| | | 32..63 | shutter open |
| | | 64..95 | Strobe effect slow to fast |
| | | 96..127 | shutter open |
| | | 128..159 | Pulse-effect in sequences slow to fast |
| | | 160..191 | shutter open |
| | | 192..223 | Random strobe effect slow to fast |
| 224..255 | shutter open | | |
| 10 | 10 | | Dimmer |
| | | 0..255 | Dimmer 0%...100% |
| 11 | 11 | | Focus |
| | | 0..255 | In(near) to out(far) |
| 12 | 12 | | Rrotating prism, Prism |
| | | 0..5 | OFF |
| | | 6..127 | ON |
| | | 128..189 | Forwards rotation from fast to slow |
| | | 190..193 | Prism rotation stop |
| 194..255 | Forwards rotation from fast to slow | | |
| 13 | 13 | | Speed pan/tile |
| | | 0..225 | max to min speed |
| | | 226..235 | blackout by movement |
| | | 236..245 | blackout by all wheel changing |
| 246..255 | no function | | |
| 14 | 14 | | Special function |
| | | 0..19 | No function |
| | | 20..29 | No function |
| | | 30..39 | No function |
| | | 40..79 | No function |
| | | 80..84 | All Motor reset |
| | | 85..87 | Scan motor reset |
| | | 88..90 | Colors motor reset |
| | | 91..93 | Gobo motor reset |
| | | 94..96 | no function |
| | | 97..99 | Other motor reset |
| | | 100..119 | Internal program 1 |
| | | 120..139 | Internal program 2 |
| | | 140..159 | Internal program 3 |
| | | 160..179 | Internal program 4 |
| | | 180..199 | Internal program 5 |
| 200..219 | Internal program 6 | | |
| 220..239 | Internal program 7 | | |
| 240..255 | Internal Sound program 1 | | |
| Vector Mode | | Value | Function |
| | 15 | | Color Time |
| | | 0..255 | max to min speed |
| | 16 | | Gobo Time |
| | | 0..255 | max to min speed |




Rotating Gobo Wheel



DMX Value

| | |
|--------|--------|
| Gobo 1 | 10..19 |
| Gobo 2 | 20..29 |
| Gobo 3 | 30..39 |
| Gobo 4 | 40..49 |
| Gobo 5 | 50..59 |
| Gobo 6 | 60..69 |


Static Gobo Wheel



DMX Value

| | |
|--------|----------|
| Gobo 1 | 15..29 |
| Gobo 2 | 30..44 |
| Gobo 3 | 45..39 |
| Gobo 4 | 60..74 |
| Gobo 5 | 75..89 |
| Gobo 6 | 90..104 |
| Gobo 7 | 105..119 |
| Gobo 8 | 120..134 |

Color Wheel



DMX Value

| | |
|---------|----------|
| Color 1 | 16..31 |
| Color 2 | 32..47 |
| Color 3 | 48..63 |
| Color 4 | 64..79 |
| Color 5 | 80..95 |
| Color 6 | 96..111 |
| Color 7 | 112..127 |

JMAZ LIGHTING

Address: 313 NEWQUIST PLACE STE B, CITY OF INDUSTRY, CA 91745 USA
 Phone: 1-626-380-0883 www.jmazlighting.com support@jmazlighting.com