



FX BAR 5050

DMX CHART:61/33/28/23/18/10

Mode/Channel						Value	Function
CH61	CH33	CH28	CH23	CH18	CH10		
1	1	1	1	1	1	0..255	Dimmer Dimmer 0%...100%
2	2	2	2	2	9	0..7	Warm Shutter shutter open
						8..255	Strobe effect slow to fast
3	3	3	3	3	6	0..255	Warm 1 0-100% Warm 1 dimmer from dark to bright
4						0..255	Warm 2 0-100% Warm 2 dimmer from dark to bright
5						0..255	Warm 3 0-100% Warm 3 dimmer from dark to bright
6	4	4	4	3	6	0..255	Warm 4 0-100% Warm 4 dimmer from dark to bright
7						0..255	Warm 5 0-100% Warm 5 dimmer from dark to bright
8	5	4	4	3	6	0..255	Warm 6 0-100% Warm 6 dimmer from dark to bright
9						0..255	Warm 7 0-100% Warm 7 dimmer from dark to bright
10						0..255	Warm 8 0-100% Warm 8 dimmer from dark to bright
11	6	5	4	3	6	0..255	Warm 9 0-100% Warm 9 dimmer from dark to bright
12						0..255	Warm 10 0-100% Warm 10 dimmer from dark to bright
13	7	6	5	4	6	0..255	Warm 11 0-100% Warm 11 dimmer from dark to bright
14						0..255	Warm 12 0-100% Warm 12 dimmer from dark to bright
15	7	6	5	4	6	0..255	Warm Macro No Function
						0..20	No Function
						21..30	Warm Macro Scene1
						31..40	Warm Macro Scene2
						41..50	Warm Macro Scene3
						51..60	Warm Macro Scene4
						61..70	Warm Macro Scene5
						71..80	Warm Macro Scene6
						81..90	Warm Macro Scene7
						91..100	Warm Macro Scene8
						101..110	Warm Macro Scene9
						111..120	Warm Macro Scene10
						121..130	Warm Macro Scene11
						131..140	Warm Macro Scene12
						141..150	Warm Macro Scene13
						151..160	Warm Macro Scene14
						161..170	Warm Macro Scene15
171..180	Warm Macro Scene16						
181..190	Warm Macro Scene17						
191..200	Warm Macro Scene18						
201..210	Warm Macro Scene19						
211..220	Warm Macro Scene20						
221..230	Warm Macro Sound1						
231..240	Warm Macro Sound2						
241..250	Warm Macro Sound3						
251..255	Warm Macro Sound4						
16	8	7	6	5		0..255	Warm Macro_Speed Warm Macro Speed from Slow to Fast



17	9	8	7	6	9		Cold Shutter
						0..7	shutter open
						8..255	Strobe effect slow to fast
18	10	9	8	7	5	0..255	Cold 1 0-100% Cold 1 dimmer from dark to bright
19						0..255	Cold 2 0-100% Cold 2 dimmer from dark to bright
20						0..255	Cold 3 0-100% Cold 3 dimmer from dark to bright
21						0..255	Cold 4 0-100% Cold 4 dimmer from dark to bright
22	11	10	9	7	5	0..255	Cold 5 0-100% Cold 5 dimmer from dark to bright
23						0..255	Cold 6 0-100% Cold 6 dimmer from dark to bright
24	12	11	9	7	5	0..255	Cold 7 0-100% Cold 7 dimmer from dark to bright
25						0..255	Cold 8 0-100% Cold 8 dimmer from dark to bright
26						0..255	Cold 9 0-100% Cold 9 dimmer from dark to bright
27						0..255	Cold 10 0-100% Cold 10 dimmer from dark to bright
28	13	11	9	7	5	0..255	Cold 11 0-100% Cold 11 dimmer from dark to bright
29						0..255	Cold 12 0-100% Cold 12 dimmer from dark to bright
30	14	12	10	8			Cold Macro
						0..20	No Function
						21..30	Cold Macro Scene1
						31..40	Cold Macro Scene2
						41..50	Cold Macro Scene3
						51..60	Cold Macro Scene4
						61..70	Cold Macro Scene5
						71..80	Cold Macro Scene6
						81..90	Cold Macro Scene7
						91..100	Cold Macro Scene8
						101..110	Cold Macro Scene9
						111..120	Cold Macro Scene10
						121..130	Cold Macro Scene11
						131..140	Cold Macro Scene12
						141..150	Cold Macro Scene13
						151..160	Cold Macro Scene14
						161..170	Cold Macro Scene15
171..180	Cold Macro Scene16						
181..190	Cold Macro Scene17						
191..200	Cold Macro Scene18						
201..210	Cold Macro Scene19						
211..220	Cold Macro Scene20						
221..230	Cold Macro Sound1						
231..240	Cold Macro Sound2						
241..250	Cold Macro Sound3						
251..255	Cold MacroSound4						
31	15	13	11	9			Cold Macro_Speed
						0..255	Cold Macro Speed from Slow to Fast
32	16	14	12	10	9		Lamp Shutter
						0..7	shutter open
						8..255	Strobe effect slow to fast



33	17	15	13	11	2		Lamp_Red 1
						0..255	0-100% Lamp_Red 1 dimmer from dark to bright
34	18	16	14	12	3		Lamp_Green 1
						0..255	0-100% Lamp_Green 1 dimmer from dark to bright
35	19	17	15	13	4		Lamp_Blue 1
						0..255	0-100% Lamp_Blue 1 dimmer from dark to bright
36	17	15	13	11	2		Lamp_Red 2
						0..255	0-100% Lamp_Red 2 dimmer from dark to bright
37	18	16	14	12	3		Lamp_Green 2
						0..255	0-100% Lamp_Green 2 dimmer from dark to bright
38	19	17	15	13	4		Lamp_Blue 2
						0..255	0-100% Lamp_Blue 2 dimmer from dark to bright
39	20	15	13	11	2		Lamp_Red 3
						0..255	0-100% Lamp_Red 3 dimmer from dark to bright
40	21	16	14	12	3		Lamp_Green 3
						0..255	0-100% Lamp_Green 3 dimmer from dark to bright
41	22	17	15	13	4		Lamp_Blue 3
						0..255	0-100% Lamp_Blue 3 dimmer from dark to bright
42	20	18	13	11	2		Lamp_Red 4
						0..255	0-100% Lamp_Red 4 dimmer from dark to bright
43	21	19	14	12	3		Lamp_Green 4
						0..255	0-100% Lamp_Green 4 dimmer from dark to bright
44	22	20	15	13	4		Lamp_Blue 4
						0..255	0-100% Lamp_Blue 4 dimmer from dark to bright
45	23	18	16	11	2		Lamp_Red 5
						0..255	0-100% Lamp_Red 5 dimmer from dark to bright
46	24	19	17	12	3		Lamp_Green 5
						0..255	0-100% Lamp_Green 5 dimmer from dark to bright
47	25	20	18	13	4		Lamp_Blue 5
						0..255	0-100% Lamp_Blue 5 dimmer from dark to bright
48	23	21	16	11	2		Lamp_Red 6
						0..255	0-100% Lamp_Red 6 dimmer from dark to bright
49	24	22	17	12	3		Lamp_Green 6
						0..255	0-100% Lamp_Green 6 dimmer from dark to bright
50	25	23	18	13	4		Lamp_Blue 6
						0..255	0-100% Lamp_Blue 6 dimmer from dark to bright
51	26	21	16	11	2		Lamp_Red 7
						0..255	0-100% Lamp_Red 7 dimmer from dark to bright
52	27	22	17	12	3		Lamp_Green 7
						0..255	0-100% Lamp_Green 7 dimmer from dark to bright
53	28	23	18	13	4		Lamp_Blue 7
						0..255	0-100% Lamp_Blue 7 dimmer from dark to bright
54	26	21	16	11	2		Lamp_Red 8
						0..255	0-100% Lamp_Red 8 dimmer from dark to bright
55	27	22	17	12	3		Lamp_Green 8
						0..255	0-100% Lamp_Green 8 dimmer from dark to bright
56	28	23	18	13	4		Lamp_Blue 8
						0..255	0-100% Lamp_Blue 8 dimmer from dark to bright
57	29	24	19	14			Lamp_Macro
						0..20	No Function
						21..35	Lamp Macro Scene1
						36..50	Lamp Macro Scene2
						51..65	Lamp Macro Scene3
						66..80	Lamp Macro Scene4
						81..95	Lamp Macro Scene5
						96..110	Lamp Macro Scene6
						111..125	Lamp Macro Scene7
						126..140	Lamp Macro Scene8
141..155	Lamp Macro Scene9						



						156..170	Lamp Macro Scene10
						171..185	Lamp Macro Scene11
						186..200	Lamp Macro Scene12
						201..215	Lamp Macro Sound1
						216..230	Lamp Macro Sound2
						231..245	Lamp Macro Sound3
						246..255	Lamp MacroSound4
58	30	25	20	15			Lamp Macro_Speed
						0..255	Lamp Macro Speed from Slow to Fast
59	31	26	21	16	7		All Macro
						0..25	No Function
						26..48	All Macro Scene1
						49..71	All Macro Scene2
						72..94	All Macro Scene3
						95..117	All Macro Scene4
						118..140	All Macro Scene5
						141..163	All Macro Scene6
						164..186	All Macro Scene7
						187..209	All Macro Scene8
						210..232	All Macro Scene9
						233..255	All Macro Scene10
60	32	27	22	17	8		All Macro_Speed
						0..255	All Macro Speed from Slow to Fast
61	33	28	23	18	10		All Sound Macro
						0..25	No Function
						26..54	All Macro Sound1
						55..83	All Macro Sound2
						84..112	All Macro Sound3
						113..141	All Macro Sound4
						142..170	All Macro Sound5
						171..199	All Macro Sound6
						200..228	All Macro Sound7
						229..255	All Macro Sound8

JMAZ LIGHTING

Address: 2422 Lee Ave, South El Monte, CA 91733

Phone:1-626-380-0883 www.jmazlighting.com support@jmazlighting.com