

Mode/Channel		Value	Function	
CH38	CH12(Default) CH06			
1	1	1	<b>Red</b>	
			0..255	0-100% Red dimmer from dark to bright
2	2	2	<b>Green</b>	
			0..255	0-100% Green dimmer from dark to bright
3	3	3	<b>Blue</b>	
			0..255	0-100% Blue dimmer from dark to bright
4	4	4	<b>White</b>	
			0..255	0-100% White dimmer from dark to bright
5	5	5	<b>Amber</b>	
			0..255	0-100% Amber dimmer from dark to bright
6	6	6	<b>UV</b>	
			0..255	0-100% UV dimmer from dark to bright
7	7		<b>Master Dimmer</b>	
			0..255	Dimmer 0%...100%
8	8		<b>Master Shutter</b>	
			0..31	Shutter closed
			32..63	shutter open
			64..95	Strobe effect slow to fast
			96..127	shutter open
			128..159	Pulse effect in sequences slow to fast
			160..191	shutter open
			192..223	Random strobe effect slow to fast
224..255	shutter open			
9	9		<b>Macro Color</b>	
			0..3	No Function
			4..7	Red
			8..11	Green
			12..15	Blue
			16..19	White
			20..23	R+G
			24..27	R+B
			28..31	R+W
			32..35	R+A
			36..39	R+UV
			40..41	G+B
			44..47	G+W
			48..51	G+A
			52..55	G+UV
			56..59	B+W
			60..63	B+A
			64..67	B+UV
			68..71	W+A
			72..75	W+UV
76..79	A+UV			
80..83	R+G+B			
84..87	R+G+W			
88..91	R+G+A			

9	9	92..95	R+G+UV
		96..99	R+B+W
		100..103	R+B+A
		104..107	R+B+UV
		108..111	R+W+A
		112..115	R+W+UV
		116..119	R+A+UV
		120..123	G+B+W
		124..127	G+B+A
		128..131	G+B+UV
		132..135	G+W+A
		136..140	G+W+UV
		140..143	G+A+UV
		144..147	B+W+A
		148..151	B+W+UV
		152..155	B+A+UV
		156..159	W+A+UV
		160..163	R+G+B+W
		164..167	R+G+B+A
		168..171	R+G+B+UV
		172..175	R+G+B+A
		176..179	R+G+W+UV
		180..183	R+G+A+UV
		184..187	R+W+UV
		188..191	R+A+UV
		192..195	R+B+W+A
		196..199	R+B+W+UV
		200..203	R+B+A+UV
		204..207	R+W+A+UV
		208..211	G+B+W+A
		212..215	G+B+W+UV
		216..219	G+B+A+UV
		220..223	G+W+A+UV
		224..227	B+W+A+UV
228..231	R+G+B+W+A		
232..235	R+G+B+W+UV		
236..239	R+G+B+A+UV		
240..243	R+G+W+A+UV		
244..247	R+B+W+A+UV		
248..251	G+B+W+A+UV		
252..255	R+G+B+W+A+UV		
10	10		Color Temp
		0..15	No Function
		16..45	Below 3200K
		46..75	3200K- 3500K
		76..105	3500K- 5000K
		106..135	5000K- 5500K
		136..165	5500K- 6000K
		166..195	6000K- 6500K
		196..225	6500K- 7000K
226..255	7000K- 8000K		

11	11		<b>Macro RUN</b>
		0..15	No function
		16..21	Macro Run 1
		22..27	Macro Run 2
		28..33	Macro Run 3
		34..39	Macro Run 4
		40..45	Macro Run 5
		46..51	Macro Run 6
		52..57	Macro Run 7
		58..63	Macro Run 8
		64..69	Macro Run 9
		70..75	Macro Run 10
		76..81	Macro Run 11
		82..87	Macro Run 12
		88..93	Macro Run 13
		94..99	Macro Run 14
		100..105	Macro Run 15
		106..111	Macro Run 16
		112..117	Macro Run 17
		118..123	Macro Run 18
		124..129	Macro Run 19
		130..135	Macro Sound1
		136..141	Macro Sound2
		142..147	Macro Sound3
		148..153	Macro Sound4
		154..159	Macro Sound5
		160..165	Macro Sound6
		166..171	Macro Sound7
		172..177	Macro Sound8
		178..183	Macro Sound9
184..189	Macro Sound10		
190..195	Macro Sound11		
196..201	Macro Sound12		
202..207	Macro Sound13		
208..213	Macro Sound14		
214..219	Macro Sound15		
220..225	Macro Sound16		
226..231	Macro Sound17		
232..255	Macro Sound18		
12	12		<b>Macro Speed</b>
		0..255	Macro Speed from Slow To Fast
13			<b>Red1</b>
		0..255	0-100% Red1 dimmer from dark to bright
14			<b>Green1</b>
		0..255	0-100% Green1 dimmer from dark to bright
15			<b>Blue1</b>
		0..255	0-100% Blue1 dimmer from dark to bright
16			<b>White1</b>
		0..255	0-100% White1 dimmer from dark to bright

17				<b>Amber1</b>
		0..255		0-100% Amber1 dimmer from dark to bright
18				<b>UV1</b>
		0..255		0-100% UV1 dimmer from dark to bright
19				<b>Ring 1 Dimmer (if MasterDimmer = 0)</b>
		0..255		Ring 1 Dimmer 0%...100%
				<b>Ring 1 Shutter (if MasterShutter = 0)</b>
		0..31		Shutter closed
		32..63		shutter open
		64..95		Strobe effect slow to fast
		96..127		shutter open
		128..159		Pulse-effect in sequences slow to fast
		160..191		shutter open
		192..223		Random strobe effect slow to fast
		224..255		shutter open
21				<b>Red2</b>
		0..255		0-100% Red2 dimmer from dark to bright
22				<b>Green2</b>
		0..255		0-100% Green2 dimmer from dark to bright
23				<b>Blue2</b>
		0..255		0-100% Blue2 dimmer from dark to bright
24				<b>White2</b>
		0..255		0-100% White2 dimmer from dark to bright
25				<b>Amber2</b>
		0..255		0-100% Amber2 dimmer from dark to bright
26				<b>UV2</b>
		0..255		0-100% UV2 dimmer from dark to bright
27				<b>Ring 2 Dimmer (if MasterDimmer = 0)</b>
		0..255		Ring 2 Dimmer 0%...100%
				<b>Ring 2 Shutter (if MasterShutter = 0)</b>
		0..31		Shutter closed
		32..63		shutter open
		64..95		Strobe effect slow to fast
		96..127		shutter open
		128..159		Pulse-effect in sequences slow to fast
		160..191		shutter open
		192..223		Random strobe effects slow to fast
		224..255		shutter open
29				<b>Red3</b>
		0..255		0-100% Red3 dimmer from dark to bright
30				<b>Green3</b>
		0..255		0-100% Green3 dimmer from dark to bright
31				<b>Blue3</b>
		0..255		0-100% Blue3 dimmer from dark to bright
32				<b>White3</b>
		0..255		0-100% White3 dimmer from dark to bright

33				<b>Amber3</b>
			0..255	0-100% Amber3 dimmer from dark to bright
34				<b>UV3</b>
			0..255	0-100% UV3 dimmer from dark to bright
35				<b>Ring 3 Dimmer (if Master Dimmer = 0)</b>
			0..255	Ring 3 Dimmer 0%...100%
				<b>Ring 3 Shutter (if Master Shutter = 0)</b>
			0..31	Shutter closed
			32..63	shutter open
			64..95	Strobe effect slow to fast
			96..127	shutter open
			128..159	Pulse effect in sequences slow to fast
			160..191	shutter open
			192..223	Random strobe effect slow to fast
			224..255	shutter open
				Custom colors Macro
			0..15	No Function
			16..55	Custom colors Macro1
			56..95	Custom colors Macro2
			96..135	Custom colors Macro3
			136..175	Custom colors Macro4
			176..215	Custom colors Macro5
			216..255	Custom colors Macro6
				<b>Custom colors Macro Speed</b>
38			0..255	Custom colors Macro Speed from Slow To Fast