

Channel Mode: 6CH

CHANNEL	FUCNTION	VALUE	DESCRIPTION
1	Master Dimmer	0	NO
		1-255	Dark to Bright
2	Strobe	1-255	<p>0-5: Shut Mode 1: 006-255 Speed from Slow to Fast Mode 2: 006-053: Fast forward and Fast out, Slow to Fast 054-103: Fast forward and Slow out, slow to fast 104-153: Slow forward and Fast out, slow to fast 154-203: Slow forward and Slow out, slow to fast 204-255: Pulse strobe, slow to fast</p>
3	Red Dimmer	0	NO
		1-255	Dark to Bright
4	Green Dimmer	0	NO
		1-255	Dark to Bright
5	Blue Dimmer	0	NO
		1-255	Dark to Bright
6	White Dimmer	0	NO
		1-255	Dark to Bright

Channel Mode: 9CH

CHANNEL	FUCNTION	VALUE	DESCRIPTION
1	Master Dimmer	0	NO
		1-255	Dark to Bright
2	Strobe	1-255	0-5: Shut Mode 1: 006-255 Speed from Slow to Fast Mode 2: 006-053: Fast forward and Fast out, Slow to Fast 054-103: Fast forward and Slow out, slow to fast 104-153: Slow forward and Fast out, slow to fast 154-203: Slow forward and Slow out, slow to fast 204-255: Pulse strobe, slow to fast
3	Built-in Pro	0-255	000-015: Shut; 016-031: Pro 1; 032-047: Pro 2; 048-063: Pro 3; 064-079: Pro 4; 080-095: Pro 5; 096-111: Pro 6; 112-127: Pro 7; 128-143: Pro 8; 144-159: Pro 9; 160-175: Pro 10; 176-191: Pro 11; 192-207: Pro 12; 208-223: Pro 13; 224-239: Pro 14; 240-255: Pro 15;
4	Speed for Built-in Pro	0-199	Fast to Slow
		200-255	Sound Mode Sensitivity from Low to High
5	Color Built-in Pro	0-255	000-015: Shut 016-031: R 032-047: G 048-063: B 064-079: W 080-095: RG 096-111: RB 112-127: RW 128-143: GB 144-159: BW 160-175: GW - 176-191: RGB 192-207: RGW 208-223: RBW 224-239: GBW 240-255: RGBW
6	Red Dimmer	0	NO
		1-255	Dark to Bright
7	Green Dimmer	0	NO
		1-255	Dark to Bright
8	Blue Dimmer	0	NO
		1-255	Dark to Bright
9	White Dimmer	0	NO
		1-255	Dark to Bright

Channel Mode: 36CH

RING 1

CHANNEL	FUCNTION	VALUE	DESCRIPTION
1	Red	0-255	Red Ring 1 (Small Ring) 0 - Shut 1 - 255 Dark to Bright
2	Green	0-255	Green Ring 1 (Small Ring) 0 - Shut 1 - 255 Dark to Bright
3	Blue	0-255	Blue Ring 1 (Small Ring) 0 - Shut 1 - 255 Dark to Bright
4	White	0-255	White Ring 1 (Small Ring) 0 - Shut 1 - 255 Dark to Bright

RING 2

5	Red	0-255	Red Ring 2 0 - Shut 1 - 255 Dark to Bright
6	Green	0-255	Green Ring 2 0 - Shut 1 - 255 Dark to Bright
7	Blue	0-255	Blue Ring 2 0 - Shut 1 - 255 Dark to Bright
8	White	0-255	White Ring 2 0 - Shut 1 - 255 Dark to Bright

RING 3

9	Red	0-255	Red Ring 3 0 - Shut 1 - 255 Dark to Bright
10	Green	0-255	Green Ring 3 0 - Shut 1 - 255 Dark to Bright
11	Blue	0-255	Blue Ring 3 0 - Shut 1 - 255 Dark to Bright
12	White	0-255	White Ring 3 0 - Shut 1 - 255 Dark to Bright

RING 4

13	Red	0-255	Red Ring 4 0 - Shut 1 - 255 Dark to Bright
14	Green	0-255	Green Ring 4 0 - Shut 1 - 255 Dark to Bright
15	Blue	0-255	Blue Ring 4 0 - Shut 1 - 255 Dark to Bright
16	White	0-255	White Ring 4 0 - Shut 1 - 255 Dark to Bright

RING 5

17	Red	0-255	Red Ring 5 0 - Shut 1 - 255 Dark to Bright
18	Green	0-255	Green Ring 5 0 - Shut 1 - 255 Dark to Bright
19	Blue	0-255	Blue Ring 5 0 - Shut 1 - 255 Dark to Bright
20	White	0-255	White Ring 5 0 - Shut 1 - 255 Dark to Bright

RING 6	21	Red	0-255	Red Ring 6 0 - Shut 1 - 255 Dark to Bright
	22	Green	0-255	Green Ring 6 0 - Shut 1 - 255 Dark to Bright
	23	Blue	0-255	Blue Ring 6 0 - Shut 1 - 255 Dark to Bright
	24	White	0-255	White Ring 6 0 - Shut 1 - 255 Dark to Bright
RING 7	25	Red	0-255	Red Ring 7 0 - Shut 1 - 255 Dark to Bright
	26	Green	0-255	Green Ring 7 0 - Shut 1 - 255 Dark to Bright
	27	Blue	0-255	Blue Ring 7 0 - Shut 1 - 255 Dark to Bright
	28	White	0-255	White Ring 7 0 - Shut 1 - 255 Dark to Bright
RING 8	29	Red	0-255	Red Ring 8 0 - Shut 1 - 255 Dark to Bright
	30	Green	0-255	Green Ring 8 0 - Shut 1 - 255 Dark to Bright
	31	Blue	0-255	Blue Ring 8 0 - Shut 1 - 255 Dark to Bright
	32	White	0-255	White Ring 8 0 - Shut 1 - 255 Dark to Bright
RING 9	33	Red	0-255	Red Ring 9 0 - Shut 1 - 255 Dark to Bright
	34	Green	0-255	Green Ring 9 0 - Shut 1 - 255 Dark to Bright
	35	Blue	0-255	Blue Ring 9 0 - Shut 1 - 255 Dark to Bright
	36	White	0-255	White Ring 9 0 - Shut 1 - 255 Dark to Bright

Channel Mode: 41CH

CHANNEL	FUCNTION	VALUE	DESCRIPTION
1	Master Dimmer	0	NO
		1-255	Dark to Bright
2	Strobe	1-255	0-5: Shut Mode 1: 006-255 Speed from Slow to Fast Mode 2: 006-053: Fast forward and Fast out, Slow to Fast 054-103: Fast forward and Slow out, slow to fast 104-153: Slow forward and Fast out, slow to fast 154-203: Slow forward and Slow out, slow to fast 204-255: Pulse strobe, slow to fast
3	Built-in Pro	0-255	000-015: Shut; 016-031: Pro 1; 032-047: Pro 2; 048-063: Pro 3; 064-079: Pro 4; 080-095: Pro 5; 096-111: Pro 6; 112-127: Pro 7; 128-143: Pro 8; 144-159: Pro 9; 160-175: Pro 10; 176-191: Pro 11; 192-207: Pro 12; 208-223: Pro 13; 224-239: Pro 14; 240-255: Pro 15;
4	Speed for Built-in Pro	0-199	Fast to Slow
		200-255	Sound Mode Sensitivity from Low to High
5	Color Built-in Pro	0-255	000-015: Shut 016-031: R 032-047: G 048-063: B 064-079: W 080-095: RG 096-111: RB 112-127: RW 128-143: GB 144-159: BW 160-175: GW - 176-191: RGB 192-207: RGW 208-223: RBW 224-239: GBW 240-255: RGBW

RING 1	6	Red	0-255	Red Ring 1 0 - Shut 1 - 255 Dark to Bright
	7	Green	0-255	Green Ring 1 0 - Shut 1 - 255 Dark to Bright
	8	Blue	0-255	Blue Ring 1 0 - Shut 1 - 255 Dark to Bright
	9	White	0-255	White Ring 1 0 - Shut 1 - 255 Dark to Bright
RING 2	10	Red	0-255	Red Ring 2 0 - Shut 1 - 255 Dark to Bright
	11	Green	0-255	Green Ring 2 0 - Shut 1 - 255 Dark to Bright
	12	Blue	0-255	Blue Ring 2 0 - Shut 1 - 255 Dark to Bright
	13	White	0-255	White Ring 2 0 - Shut 1 - 255 Dark to Bright
RING 3	14	Red	0-255	Red Ring 3 0 - Shut 1 - 255 Dark to Bright
	15	Green	0-255	Green Ring 3 0 - Shut 1 - 255 Dark to Bright
	16	Blue	0-255	Blue Ring 3 0 - Shut 1 - 255 Dark to Bright
	17	White	0-255	White Ring 3 0 - Shut 1 - 255 Dark to Bright
RING 4	18	Red	0-255	Red Ring 4 0 - Shut 1 - 255 Dark to Bright
	19	Green	0-255	Green Ring 4 0 - Shut 1 - 255 Dark to Bright
	20	Blue	0-255	Blue Ring 4 0 - Shut 1 - 255 Dark to Bright
	21	White	0-255	White Ring 4 0 - Shut 1 - 255 Dark to Bright
RING 5	22	Red	0-255	Red Ring 5 0 - Shut 1 - 255 Dark to Bright
	23	Green	0-255	Green Ring 5 0 - Shut 1 - 255 Dark to Bright
	24	Blue	0-255	Blue Ring 5 0 - Shut 1 - 255 Dark to Bright
	25	White	0-255	White Ring 5 0 - Shut 1 - 255 Dark to Bright

RING 6	26	Red	0-255	Red Ring 6 0 - Shut 1 - 255 Dark to Bright
	27	Green	0-255	Green Ring 6 0 - Shut 1 - 255 Dark to Bright
	28	Blue	0-255	Blue Ring 6 0 - Shut 1 - 255 Dark to Bright
	29	White	0-255	White Ring 6 0 - Shut 1 - 255 Dark to Bright
RING 7	30	Red	0-255	Red Ring 7 0 - Shut 1 - 255 Dark to Bright
	31	Green	0-255	Green Ring 7 0 - Shut 1 - 255 Dark to Bright
	32	Blue	0-255	Blue Ring 7 0 - Shut 1 - 255 Dark to Bright
	33	White	0-255	White Ring 7 0 - Shut 1 - 255 Dark to Bright
RING 8	34	Red	0-255	Red Ring 8 0 - Shut 1 - 255 Dark to Bright
	35	Green	0-255	Green Ring 8 0 - Shut 1 - 255 Dark to Bright
	36	Blue	0-255	Blue Ring 8 0 - Shut 1 - 255 Dark to Bright
	37	White	0-255	White Ring 8 0 - Shut 1 - 255 Dark to Bright
RING 9	38	Red	0-255	Red Ring 9 0 - Shut 1 - 255 Dark to Bright
	39	Green	0-255	Green Ring 9 0 - Shut 1 - 255 Dark to Bright
	40	Blue	0-255	Blue Ring 9 0 - Shut 1 - 255 Dark to Bright
	41	White	0-255	White Ring 9 0 - Shut 1 - 255 Dark to Bright