

Channel Mode: 1CH

1 Channel Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer

Channel Mode: 2CH

2 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Strobe	000-255: Strobe with speed increasing

Channel Mode: 3CH

3 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Dimmer fine	000-255: 16 bit dimmer
CH3	Strobe	000-255: Strobe with speed increasing